



WAAY Panel Operation


POWER ON/CALIBRATE

Step 1:




Slide button on the bottom of the inside panel to the right to power on the WAAY Smart Door System.

Step 2:



Press the Lock button on your panel or the remote to Calibrate.

Step 3:



Your door is now calibrating.

SETTINGS>General



Enable or disable to sync the time over the network



Select your Timezone



- 12 Hour
- 24 Hour



- Enable
- Disable



- Imperial
- Metric



Can manually be changed if network time is disabled



Can manually be changed if network time is disabled

SETTINGS>WIFI



Press the right arrow on your remote to connect




Iphone: Scan QR Code with camera, and then click join. Open settings/wifi on your phone and click the WAAY_XXXX network. A screen will open and select the wifi you would like to have the door connected to. Enter your wifi password, and your door is now setup.


Android: Scan QR Code with google lens, then click join network and select WAAY_XXXX. A screen will open and select the wifi you would like to have the door connected to. Enter your wifi password, and your door is now setup.

SETTINGS>Door Motion

*The WAAY Smart System is fully operational with or without wifi



- WAAY Fast
- Faster
- Fast
- Normal
- Slow
- Waay Quiet



- Fast
- Normal
- Slow



Move Door to set and save your desired Open Position



Door will automatically close after opening:

- Never
- 5 Seconds
- 10 Seconds
- 20 Seconds
- 30 Seconds
- 60 Seconds
- 2 Minutes
- 10 Minutes



WAAY Panel Operation

SETTINGS>Panels



- Both Sides
- This Side
- Other Side
- Disabled




Hand over Panel:

- Lock
- Unlock
- Toggle Lock
- Open
- Close
- Toggle Door
- Do Nothing



- Timeout
- Screensaver
- Motion Detect

SETTINGS>Sensors



- Enable
- Disable



- Enable
- Disable




- Enable
- Disable




- Enable
- Disable

SETTINGS>Remote



- Enable
- Disable



- Enable
- Disable



- Enable
- Disable



- Enable
- Disable




- Enable
 - Disable
- (If enabled up and down button will make door slowly open and close)

SETTINGS>About



Displays the current firmware version



Serial Number tied to your account



Displays your WAAY Account number



- Time
- Door
- Cycles
- Power
- Cycles



Press middle button to factory reset



Press middle button to check for updates (your door must be on wifi to update)